

Reactel, Incorporated

Reacting First to All Your Filter Needs.

PCS Fullband Receive Cavity Bandpass Filter

8C9-1880-X60N11

Reactel is proud to present this bandpass filter as another member of the growing family of wireless band products. This particular unit is a PCS Fullband Receive filter with a passband of 1850 – 1910 MHz. Reactel has a large variety of wireless band filters and multiplexers; please contact the factory with your specifications.



Specifications

Center Frequency	1880 MHz
Passband	1850 – 1910 MHz, minimum
Insertion Loss	≤ 0.8 dB @ Passband
Return Loss	≥ 16 dB @ Passband
Attenuation	≥ 60 dB @ 1930 – 1990 MHz
Connectors	Type N Female in / out
Size	1.75" high x 2.75" wide x 5.5" long, nominal excluding connectors

8031 Cessna Avenue • Gaithersburg, Maryland 20879
Phone: 301-519-3660 • Fax: 301-519-2447 • reactel@reactel.com • www.reactel.com
twitter: <http://twitter.com/reacteljim> • ISO 9001:2008 Accredited

Picture shown above may not be an actual representation of the unit described.