

Bandpass Filter

4C11-8531-154S11

This bandpass filter covers 8454 – 8608 MHz with low insertion loss.



Specifications

CF	8531 MHz
Passband	8454 – 8608 MHz, minimum
Insertion Loss	≤ 1.2 dB @ CF
Rejection	≥ 60 dB @ CF ± 400 to CF + 2800 MHz ≥ 60 dB @ CF + 400 MHz to 2.5 x CF
VSWR	$\leq 1.5:1$ @ CF ± 50 MHz
Connectors	SMA Female in / out
Size	0.5" high x 0.75" wide x 2.77" long, nominal excluding connectors



Reactel, Incorporated - Reacting First to Your Filter Requirements

8031 Cessna Avenue • Gaithersburg, Maryland 20879

Phone: 301-519-3660 • Fax: 301-519-2447 • reactel@reactel.com • www.reactel.com

twitter: <http://twitter.com/reacteljim>

ISO 9001:2008 Accredited

Picture shown above may not be an actual representation of the unit described.