

Reactel, Incorporated

Reacting First to All Your Filter Needs.

Wideband Highpass Filter

7HSX-18G/40G-K11

This wideband highpass filter has a passband of 18 to 40 GHz. This tiny unit is perfect for portable or “hi-rel” applications. We manufacture many different varieties of filters; please contact us with your specific need.



Specifications

3 dB Cutoff	18 GHz, nominal
Passband	Up to 40 GHz, minimum
Insertion Loss	≤ 2.0 dB @ Passband
Attenuation	≥ 30 dB @ 16 GHz
VSWR	≤ 2.5:1 @ Passband
Connectors	K Female in / out
Size	0.5" high x 0.5" wide x 1.0" long, nominal excluding connectors