

Reactel, Incorporated

Reacting First to All Your Filter Needs.

Cavity Bandpass Filter

4C3-12000-X200N11

This bandpass filter is centered at 12000 MHz with a Passband of 200 MHz and features low loss and high out of band attenuation. Reactel manufactures a wide variety of Filters, Multiplexers and Multifunction Assemblies; please contact us with your requirements.



Specifications

Center Frequency	12000 MHz
Passband	200 MHz, minimum
Insertion Loss	≤ 1.0 dB @ Passband
Power	20 W
Attenuation	≥ 40 dB @ 11000 MHz ≥ 40 dB @ 13000 MHz
Connectors	Type N Female in / out
Size	1.0" high x 1.0" wide x 2.8" long, nominal excluding connectors