

# Reactel, Incorporated

Reacting First to All Your Filter Needs.

## *Cavity Bandpass Filter*

**6C7-9250-600S11**

This cavity bandpass filter covers 8950 to 9550 MHz.



### *Specifications*

Center Frequency	9250 MHz
3 dB BW	600 MHz
Connectors	SMA Female in / out
Size	1.0" high x 1.0" wide x 4.8" long, nominal excluding connectors

8031 Cessna Avenue • Gaithersburg, Maryland 20879  
Phone: 301-519-3660 • Fax: 301-519-2447 • [reactel@reactel.com](mailto:reactel@reactel.com) • [www.reactel.com](http://www.reactel.com)  
twitter: <http://twitter.com/reacteljim> • ISO 9001:2008 Accredited

Picture shown above may not be an actual representation of the unit described.